

MA5822S Datasheet

The SmartAX MA5822S is a high-density access product for campuses launched by Huawei Technologies Co, Ltd. The MA5822S applies to fiber to the building (FTTB) or fiber to the curb (FTTC) network applications for providing voice, data, and multicast services for community users.



According to the difference of ports number, this MA5822S includes three configurations:

- 8*GE + 8*POTS
- 16*GE + 16*POTS
- 24*GE + 24*POTS


Product Highlights

- High-bandwidth access: XG-PON/XGS-PON uplink
- High port density: 8*GE+8*POTS/16*GE+16*POTS/24*GE+24*POTS
- Rich services: voice/broadband/multicast/IPv6
- Comprehensive management and maintenance: Supports one-stop deployment and plug-and-play.

Ports

Take MA5822S(24*GE+24*POTS) as an example to introduce the port type as shown in Ports of the MA5822S.

Ports of the MA5822S



Physical ports provided by the MA5822S

Port Type	Silk Screen	Description
AC power port	-	Connects to 110 V AC/220 V AC power.
Serial port	CONSOLE	Provides local and remote maintenance. Supports system configuration using tools, such as HyperTerminal, through command line interface (CLI). Supports local device management through any service port.
POTS port	POTS 1– 24	Supports POTS access and provides the VoIP, FoIP, and MoIP services.
GE electrical port	-	Provides Ethernet adaptive access rates of 10 Mbit/s, 100 Mbit/s and 1000 Mbit/s.
Upstream optical port	-	Provides XG-PON/XGS-PON/GPON upstream transmission using an SFP uplink optical port.
Grounding port	-	Connects the device to the ground.

The definition of the POTS port

X1 Pin	Port No.	X1 Pin	Port No.	Port figure	X1 Pin	Port No.	X1 Pin	Port No.
--------	-------------	--------	-------------	-------------	--------	-------------	--------	-------------

X1 Pin	Port No.		X1 Pin	Port No.	Port figure	X1 Pin	Port No.		X1 Pin	Port No.
68	24		50	8 (68 34	34	-		16	16
67			49			33			15	
66	23		48	7		32	-		14	15
65			47		88 88	31			13	
64	22		46	6		30	-	-	12	14
63			45			29			11	
62	21		44	5		28	-		10	13
61			43			27			9	
60	20		42	4	888	26	-		8	12
59			41		8888	25			7	
58	19		40 3		24	-		6	11	
57			39	_	1000	23			5	
56	18	38	2	8888	22	-		4	10	
55			37	1		21			3	
54	17	1	36	1		20	-		2	9
53			35		35 1	19			1	

Device Configuration 1: 8*GE+8*POTS

Appearance and device parameters of the MA5822S(8*GE+8*POTS)

Appearance	
Dimensions (width x depth x height)	442 mm x 220 mm x 43.6 mm (without the mounting brackets) 482.6 mm x 220 mm x 43.6 mm (with the mounting brackets)
Weight	3.08 kg
NNI	XG-PON/XGS-PON/GPON
UNI	8*GE+8*POTS
Ambient temperature	-40°C to 55°C
Ambient humidity	5% to 95%
Power Supply	100–240 V AC, 50 Hz/60 Hz
Maximum Input Current	1 A
Power consumption	Static power consumption: 28 W
	Maximum power consumption: 38 W
Protection Level	IP20

D NOTE

• In the case of the static power consumption, all ports are not activated.

• In the case of the maximum power consumption, all the broadband ports are activated and all the telephones connected to the voice ports are off-hook.

Device Configuration 2: 16*GE+16*POTS

Appearance and device parameters of the MA5822S(16*GE+16*POTS)

Appearance	
Dimensions (width x depth x height)	442 mm x 220 mm x 43.6 mm (without the mounting brackets) 482.6 mm x 220 mm x 43.6 mm (with the mounting brackets)
Weight	3.18 kg
NNI	XG-PON/XGS-PON/GPON
UNI	16*GE+16*POTS
Ambient temperature	-40°C to 55°C
Ambient humidity	5% to 95%
Power Supply	100–240 V AC, 50 Hz/60 Hz
Maximum Input Current	1 A
Power consumption	Static power consumption: 30 W Maximum power consumption: 49 W
Protection Level	IP20
Surge Protection Level	AC power 6 kV, GE 4 kV, POTS 4 kV

D NOTE

• In the case of the static power consumption, all ports are not activated.

• In the case of the maximum power consumption, all the broadband ports are activated and all the telephones connected to the voice ports are off-hook.

Device Configuration 3: 24*GE+24*POTS

Appearance and device parameters of the MA5822S(24*GE+24*POTS)

Appearance	
Dimensions (width x depth x height)	442 mm x 220 mm x 43.6 mm (without the mounting brackets) 482.6 mm x 220 mm x 43.6 mm (with the mounting brackets)
Weight	3.3 kg
NNI	XG-PON/XGS-PON/GPON
UNI	24*GE+24*POTS
Ambient temperature	-40°C to 55°C

Ambient humidity	5% to 95%
Power Supply	100–240 V AC, 50 Hz/60 Hz
Maximum Input Current	1 A
Power consumption	Static power consumption: 33 W Maximum power consumption: 62 W

D NOTE

• In the case of the static power consumption, all ports are not activated.

• In the case of the maximum power consumption, all the broadband ports are activated and all the telephones connected to the voice ports are off-hook.

QoS

•

•

•

•

•

•

•

Priority processing

Traffic Policing

Management protocol

policies

SNMP V1

SNMP V3

SNMP V2C

Traffic management

Congestion management

Access control list (ACL)

Primary Features

Upstream mode

- XG-PON
- XGS-PON
- GPON

Multicast

- IGMP v2/v3
- IGMP Proxy
- IGMP Snooping
- MLD Proxy
- MLD Snooping
- Multicast CAC

- H.248
- SIP

•

Voice

- Semi-permanent connections (SPCs)
- Voice signal processing
- Voice service test and maintenance
- Reliability of voice services

Layer 2 management

- MAC address management
- Virtual local area network (VLAN) management
- Flow Bundle
- VLAN+MAC forwarding
- Transparent transmission of protocol packets

Fault diagnosis

- Point-to-Point Protocol over Ethernet (PPPoE) dialup service emulation
- Dynamic Host Configuration Protocol (DHCP) dialup service emulation
- Multicast emulation

User security

- PITP
- DHCP Option82
- 802.1x authentication
- RAIO
- Anti-MAC address
 transfer
- Anti-MAC address spoofing
- Anti-IP address spoofing

Copyright © Huawei Technologies Co., Ltd. 2019. All rights reserved.

No part of this document may be reproduced or transmitted in any form or by any means without prior written consent of Huawei Technologies Co., Ltd.

Trademarks and Permissions

HUAWEI and other Huawei trademarks are trademarks of Huawei Technologies Co., Ltd.

All other trademarks and trade names mentioned in this document are the property of their respective holders.

Notice

The purchased products, services and features are stipulated by the contract made between Huawei and the customer. All or part of the products, services and features described in this document may not be within the purchase scope or the usage scope. Unless otherwise specified in the contract, all statements, information, and recommendations in this document are provided "AS IS" without warranties, guarantees or representations of any kind, either express or implied.

The information in this document is subject to change without notice. Every effort has been made in the preparation of this document to ensure accuracy of the contents, but all statements, information, and recommendations in this document do not constitute a warranty of any kind, express or implied.

Huawei Technologies Co., Ltd.

Address:Huawei Industrial Base Bantian, Longgang Shenzhen 518129 People's Republic of China

Website:www.huawei.com